

QUICK GUIDE



ALCATEL

*Easy*  
REFLEXES

t e l e p h o n e

# Getting to know your telephone

You have an ALCATEL Easy REFLEXES digital telephone. The screen, functions and loudspeaker combine a maximum of convenience with extremely simple operation.

## Display

The screen displays several pages of information concerning the present call.

## Programmable keys and LEDs

The keys are divided into line keys, corresponding to the line LEDs, and function keys.

### Line LEDs

- | Call in progress.
- :| Incoming call (flashing).
- :| Callback (flashing).
- :| Call on hold (flashing).

### Function LEDs

- | Function active.

### Some function keys are preprogrammed:

- Divert your calls to another extension.
- Access the various mail services.
- Access your personal directory.
- Automatically redial the last number dialled.
- Display new page.
- Transfer call to another extension.

Light indicating voice messages received or callback requests.

To terminate a call or programming.

## Audio keys

**Loudspeaker**  
to share a conversation

to reduce  
loudspeaker or  
receiver volume



to increase  
loudspeaker or  
receiver volume

## Installing the programmable key label

A printed label is supplied with the station. This should be installed between the programmable keys.


- 1 Insert a flat "blade" into the slot.
- 2 Raise the cover.
- 3 Slide the printed label into position.
- 4 Replace the cover.



To check or modify your key programming.


## SETTING UP

### Adjusting screen brightness



### Selecting ringer tune and adjusting volume

You can select your ringer tune (choice of 8) and adjust the volume (1 to 7).



### Selecting a language



### Locking/unlocking your telephone



## MAKING A CALL

### To make a call



### To answer



### To terminate a conversation



### Making an outside call



### Making an internal call



### Calling from the directory

#### Personal directory



#### Common directory



### Redialling last number dialled



### Requesting automatic callback



## HANDLING SEVERAL CALLS

### Calling a second person during a conversation

During a conversation, to call a second person.




### Receiving a second call

During a conversation, another person is trying to call you.



### Transferring a call

During a conversation, to transfer the call to another number.




### Switching between two calls (Broker call)



### Three-way conference

During a conversation, a second call is on hold.



## CUSTOMISING YOUR TELEPHONE

### Programming your personal code

The default code on your telephone is 1515.



### Programming your personal directory

Create your directory using the 10 keys (0 to 9) on the keypad.



\*To enter a name: the numeric keys have letters which can be obtained by consecutive presses.



Personal directory numbers	
0	5
1	6
2	7
3	8
4	9

## GROUP OPERATION

### Call pick-up

- Another telephone is ringing



code for function

"Extension call pick-up"



n° of telephone ringing

- A telephone in your group is ringing



code for function

"Group call pick-up"

### Answering a general bell

If the operator is absent, to reply to calls to the operator:

General bell is ringing



code for function

"Answer general bell"

### Broadcasting a message to a group

To broadcast a message on the loudspeakers of the extensions in your group:



speak: you have  
20 seconds



number of your  
broadcasting group

hang up

### Sending a written message to one of your correspondents

- Internal number



message



number of extensions  
to receive message



Call me back

first message  
in list (max. 27)



next message



previous message



read complete  
message



message sent



## WHILE YOU ARE AWAY - WHEN YOU RETURN

### Diverting calls

- To another extension



divert



destination  
number



hang up

- Diverting calls to a voicemail (option)



function code for  
type of diversion required



number of voicemail

### Follow me diversion

From extension to receive  
the diverted calls



code for function  
"Follow me diversion"



number of your extension

### Cancelling all diversions



programme another type of  
diversion

### Consulting recorded messages

The light indicates that messages have been received.

- Written messages (and callback requests)



number of  
messages



sender of  
1st message



supplementary  
information



start of  
message



remainder of  
message



call back  
sender

- Voice messages (option)



follow voice instructions

# ALCATEL OFFICE\*

## Table of codes

A function is activated by entering the corresponding code on the keypad.

Function	Default code	Your code	Function	Default code	Your code
Answer general bell	*1		Hunting group out	#4	
Answer paging by prefix	*95		Immediate diversion	*01	
Answer paging by suffix	#95		Intrude on a call	4	
Appointment time (programmed)			Line allocation		
Automatic callback if terminal busy	5		Line allocation + callback with charge info.		
Broadcast groups	**		Locking/Unlocking	*3	
Broker call	2		Meter Total Recall		
Business account code			Moving a terminal	878	
Calibrated break	65		Open door		
Cancel all diversions	*00		Operator call	9	
Cancel automatic callback	#99		Paging by prefix	#90	
Cancel enquiry call	1		Paging by suffix	7	
Cancel follow me	*07		Park / retrieve parked call	*7	
Common directory numbers	8000		Protect a call	98	
	to 8399		Redial last number	#1	
Conference	3		Replacing a terminal	877	
Consult voice messages			Seize main line	0	
Consultation of call on hold	#8		Seize secondary lines	460	
Divert group calls	#06			to 494	
Divert if busy	*02		Selective diversion		
Divert to paging	*04		Substitution		
Do not disturb	*05		(business charge code)		
Do not disturb override	9		Switch to programming	88	
DTMF End to End	#		Terminal call	100	
Follow me diversion	*06			to 227	
Group call	500		Terminal call pick-up	#6	
	to 525		Text message		
Group call pick-up	*6		(call back later)	*91	
Hunting group in	#4		Voice message	66	
			(codes reserved)	and 67	

Your telephone provides access to a number of functions, depending on your system version and configuration.

You can programme keys as required and print new labels.  
See the installation guide or contact your distributor.

Name: ..... Telephone No.: .....

Fax. No.: ..... Mobile No.: .....

E-mail address: .....

**Alcatel Business Systems, in keeping with its policy of constant product improvement for the customer, reserves the right to modify product specifications without prior notice.**

**Alcatel Business Systems - 56, avenue Jean-Jaurès - F-92707 Colombes Cedex  
R.C. Paris 602 033 185**